

20 METER VERTICAL BAZOOKA INSTALLATION - ATTACHMENT

INTERNATIONAL ANTENNA COMPANY

888-268-4214

You are the proud owner of the new **BAZOOKA VERTICAL ANTENNA**. The Vertical Bazooka can be installed along the side of a tree or a wooden support pole. The antenna will have a vertical radiation component. The feed point of the antenna must be mounted approximately ground level in reference to the vertical support (tower or tree).

If installing alongside a metal tower or metal pole the Vertical Bazooka antenna should be no closer than 24 inches. It is recommended that an insulated support be secured to the base of the tower or pole.

NOTE: If mounting to a tree or wooden pole the Vertical Bazooka can be close to the vertical support but not touching with no effect to performance.

At a point's between 5-15 feet above the "T" mold feed point connection install an insulated support that will keep the antenna 24 inches away from the metal tower or pole.

Install the vertical portion of the antenna first to the bottom insulated support point then to the top support point. This part of the antenna should be parallel and equally 24 inches from the support tower or pole.

NOTE: If mounting to a tree or wooden pole the Vertical Bazooka can be close to the vertical support but not touching with no effect to performance.

Next, install several quarter wavelength ground radials to "T" mold ground connector. Also, install an approved electrical code ground rod and secure to the ground connector.

After completing antenna mounting, connect a 50 ohm feed line such as RG-58, RG-8 or RG-213 coax to the antenna feed point and your transmitter. Carefully load the transmitter into a dummy load (not provided). Then with a very low amount of output power applied to the antenna at your desired frequency, measure the SWR. The antenna should exhibit an SWR of less than 2:1 across the entire 20-meter band.

If the SWR is higher than 2:1 be sure the antenna is well grounded to the ground radials and ground rod. It is recommended that at least 4 or more ground radials be installed at the base of the antenna.

To lower the SWR, fold the 300-ohm twin lead back on itself ensuring it is flat on itself with no gaps equally on each side and secure with ty-wraps. The fold of 6, 12, 18 or 24 inches must be done in a single fold over. The loop you have created is the tie off point. This procedure will raise the operating frequency of the CW portion of the band. If you measure a higher SWR, make sure that the antenna is not near or touching any metal objects such as rain gutters, aluminum siding, etc.

DUE TO CERTAIN SOIL CONDITIONS A TUNER MAY BE REQUIRED TO LOWER THE SWR.

APPROXIMATE FOLDOVER OF THE 300-OHM ANTENNA END SECTION FOR CERTAIN FREQUENCIES: 14.0 MHz = (.5 feet), 14.2 MHz = (1.5 feet), 14.3 MHz = (2.0 feet). Additional adjustment may be required.

After making sure the SWR is within spec and everything is clear of the antenna. You are ready to operate and enjoy all of the great signals and DX contacts that this antenna offers. We at IAC wish you the greatest DX'ing and are sure you will be pleased with your purchase.

IAC ACCEPTS NO LIABILITY FOR DAMAGE OR INJURY RESULTING FROM THE INSTALLATION AND USE OF THIS ANTENNA

Vertical Bazooka Mounting Configuration

